

FN-LCD-N - LCD NETWORK ANNUNCIATOR



DESCRIPTION

The FN-LCD-N type LCD network annunciator is de-signed to be used with the FireNET® digital analog addressable system. It allows for remote access, monitoring, and control of the FireNET® system throughout the building.

The FN-LCD-N is a true network annunciator that can access, monitor, and control any or all FireNET® panels in the network. Each FN-LCD-N is completely independent. The highly intuitive user interface and 320 character LCD display of the FN-LCD-N is exactly the same as the FireNET® panel. In addition to routing any panel in the network to the FN-LCD-N, every event category within each panel can also be individually routed, as well as routing of all remote control functions (reset, alarm silence, re-sound alarm) from individual panels. The FN-LCD-N supports the same RS485 expansion port as the FireNET® panel, allowing for FireNET® expansion boards and accessories to be connected to the network annunciator.

The FN-LCD-N also has (4) output relays for fire, supervisory, trouble & auxiliary. The relays are programmable (except supervisory).

Security is established by the use of a password or firefighters enable key. Designed to be aesthetically pleasing, the FN-LCD-N is available in red or gray and can be surface or flush mounted using a standard trim ring kit.

STANDARD FEATURES

- UL 864 9th Edition Listed
- 320 character liquid crystal display (8 line x 40 character)
- LED indicators for Fire, Supervisory Alarm, Pre-Alarm, Fire Output Active, Power On, On Test, Panel Sounder Silenced, Delay Active, More Events, Point Bypassed, General Trouble, Power Trouble, System Trouble & NAC Trouble
- Dual RS485 ports for primary fire network
- RS485 slave bus for expansion - up to 32 FN-4127-IO boards or up to 15 FN-LCD-S serial annunciators and up to 17 FN-4127-IO boards
- 2 built-in RS-232 interfaces for programming via a PC and serial printer interface
- 4 on board programmable Form C relays rated at 1 Amp at 30VDC (Fire, Supervisory, Trouble & Auxiliary)
- Same controls as the FireNET® fire panel (Reset, Panel Sounder Silence, Lamp Test, Alarm Silence, Re-sound Alarm, Fire Drill, Programmable Function, More Events, More Fire Events, Enter & Exit)
- Local piezo sounder for event notification
- Supports user codes & firefighter key to enable access & controls
- Powered by FireNET® Aux 24VDC or UL fire listed Aux. 24VDC supply
- Available in red or gray, and can be surface or flush mounted (using trim ring)
- True network annunciator, any or all panels can be routed to the FN-LCD-N. In addition, each event category can be individually routed to the FN-LCD-N
- Up to (64) FireNET® panels & FN-LCD-N's can be networked together in any combination
- 500mA of auxiliary power available rated at 24VDC
- Auto-learn feature
- Built-in help & alarm information screens
- Fire drill function
- Each FN-LCD-N is completely independent
- The FN-LCD-N can be configured to remote reset, silence, resound, any or all panels on the network in any combination

	UL 864 9th Edition		California State
	Signaling Device		Fire Marshal
PRODUCT LISTINGS		7120-0410:165	

Specifications subject to change without notice.

Continued on back.

Hochiki America Corporation
7051 Village Drive, Suite 100, Buena Park, CA 90621-2268
Phone: 714/522-2246 Fax: 714/522-2268
Technical Support: 800-845-6692 or technicalsupport@hochiki.com



Find latest revision at www.hochiki.com

FN-LCD-N - LCD NETWORK ANNUNCIATOR

SPECIFICATIONS	
Input DC	24 VDC @ 270mA Max. (+ Aux. Power Load)
Aux. Output DC	24 VDC @ 500mA
Dimensions	14.5" W x 10" H x 3.3" D
Weight	9.4 lbs
Color	Red (optional gray)
Material	ABS/steel enclosure
Operating Temperature	32° F (0° C) 120° F (49° C)
Relative Humidity	85% RH Non-Condensing
Display	8 line x 40 character LCD (320 characters total)
Network	Dual RS485 ports (64 nodes max.)
Relay Outputs	(4) From C 1amp @ 30 VDC
PC Port	RS232
Printer Port	RS232
Expansion Port	RS232

ENGINEERING SPECIFICATION

The contractor shall furnish and install where indicated on the plans, the network annunciator model FN-LCD-N. The FN-LCD-N connects to the FireNET[®] fire alarm control panel (FACP) network. The network annunciator is capable of annunciating on its 320 character display and local buzzer, the condition of any FireNET[®] FACP or network annunciator on the network. Up to 64 FN-LCD-N network annunciators or FireNET[®] FACP's may be connected together on the network. The FN-LCD-N is UL Listed, and has surface or flush mount capability.

WIRING DIAGRAM

