

FN-LCD-S - SERIAL LCD ANNUNCIATOR



DESCRIPTION

The FN-LCD-S serial annunciator provides a convenient and cost effective remote annunciator solution. Up to 15 FN-LCD-S annunciators can be connected to the slave RS-485 port of the FireNET® control panel or network annunciator. The FN-LCD-S's large 320 character display and navigation buttons are a complete mimic of the FireNET® control panel display. The use of a common interface allows the user to easily operate the FN-LCD-S as if he were operating the FireNET® control panel directly.

Security is established by the use of a password or firefighters enable key. Designed to be aesthetically pleasing, the FN-LCD-S is available in red or gray enclosures. The FN-LCD-S can be surface or flush mounted without the need for a trim ring.

STANDARD FEATURES

- UL 864 9th Edition Listed
- Large 320 character liquid crystal display (8 line x 40 character) allows viewing of system status
- LED indicators for Fire, Supervisory Alarm, Pre-Alarm, Fire Output Active, AC Power On, On Test, Panel Sounder Silenced, Delay Active, More Events, Point Bypassed, General Trouble, Power Trouble, System Trouble & NAC Trouble
- Same controls as the FireNET® fire panel (Reset, Panel Sounder Silence, Lamp Test, Alarm Silence, Re-sound Alarm, Fire Drill, Programmable Function, More Events, More Fire Events, Enter & Exit)
- Up to 15 FN-LCD-S serial annunciators may be connected to a FireNET® control panel or network annunciator
- Resides on the FireNET® slave RS-485 line
- Local piezo sounder for event notification
- Supports user codes & firefighter key to enable access & controls
- Powered by FireNET® Aux 24VDC or UL fire listed Aux. 24VDC supply
- Available in red or gray, and can be surface or flush mounted
- Built-in help & alarm information screens
- Fire drill function

PRODUCT LISTINGS



UL 864, Local Signaling. NFPA 70, 72 & 13 Compliant



California State Fire Marshal
7120-0410:165

SPECIFICATIONS

Current Draw - Standby:	20mA @ 24VDC
Current Draw - Alarm:	110mA @ 24VDC
Dimensions - FN-LCD-S	10.88" W x 8.00" H x 1.38" D
Dimension - Back Box	10.38" W x 7.38" H x 1.25" D
Weight	3.5 lbs
Color	Red (optional gray)
Material	ABS/steel enclosure
Operating Temp.	32° F (0° C) 120° F (49° C)
Relative Humidity	85% RH Non-Condensing
Display	8 line x 40 character LCD (320 characters total)
Network	RS485 port

Specifications subject to change without notice.

Continued on back.

Hochiki America Corporation
7051 Village Drive, Suite 100, Buena Park, CA 90621-2268
Phone: 714/522-2246 Fax: 714/522-2268
Technical Support: 800-845-6692 or technicalsupport@hochiki.com



Find latest revision at www.hochiki.com

FN-LCD-S - SERIAL LCD ANNUNCIATOR

ENGINEERING SPECIFICATIONS

The contractor shall furnish and install where indicated on the plans, the serial remote annunciator model FN-LCD-S. The FN-LCD-S connects to the FireNET® fire alarm control panel (FACP) or network annunciator (FN-LCD-N) RS485 slave bus. The serial remote annunciator annunciates on its 320 character display and local buzzer, the condition of its master FireNET® FACP. Up to 15 FN-LCD-S serial annunciators may be connected together on a single RS-485 FireNET® slave bus. The FN-LCD-S is UL listed and compatible with the Hochiki FireNET® control panel, and has surface or flush mount capability.

WIRING DIAGRAM

