



## HCVR-SQA - SEQUENTIAL ACTIVATOR



### STANDARD FEATURES

- UL Listed and FM Approved
- Used to activate up to two FirePro® Xtinguish aerosol generators
- Includes a back box for surface mount (HCVR-SQA-L has larger back box for ease of wiring)
- Fault LED is illuminated to indicate trouble conditions

### DESCRIPTION

The HCVR-SQA is a sequential activator that is used to operate a fixed, condensed aerosol generator for extinguishing fire in a total-flooding fire suppression system.

### SPECIFICATIONS

Dimensions:	
HCVR-SQA-L	HCVR-SQA
7.3"W x 5.2"H x 1.8"D 186 mm x 132 mm x 47 mm	3.8"W x 3.8"H x 1.8"D 97.3 mm x 97.3 mm x 46 mm
Supply Voltage	24 VDC
Average Current Consumption	1 mA
Maximum Output Current	1 A @ 24 VDC
Material	Mild steel

### COMPATIBILITY LIST

#### Cylindrical Type

#### Box Type

#### HOCHIKI AMERICA

FNX-20 (all models except FNX-20TH)	FNX-1200 (all models)
FNX-40 (all models)	FNX-2000 (all models)
FNX-80 (all models)	FNX-3000 (all models)
FNX-100S	FNX-4200 (all models)
FNX-200S	FNX-5700 (all models)
FNX-500S	

#### FIREPRO

FP-20 (all models except FP-20TH)	FP-1200 (all models)
FP-40 (all models)	FP-2000 (all models)
FP-80 (all models)	FP-3000 (all models)
FP-100S	FP-4200 (all models)
FP-200S	FP-5700 (all models)
FP-500S	

#### PRODUCT LISTINGS



California State  
Fire Marshal  
7300-0410:0207

Specifications subject to change without notice.

Continued on back.

Hochiki America Corporation  
7051 Village Drive, Suite 100, Buena Park, CA 90621-2268  
Phone: 714/522-2246 Fax: 714/522-2268  
Technical Support: 800-845-6692 or technicalsupport@hochiki.com



Find latest revision at [www.hochiki.com](http://www.hochiki.com)

F0167 07/2019

## HCVR-SQA - SEQUENTIAL ACTIVATOR

### TYPICAL WIRING DIAGRAM

